

SLA

SINGLE LINE ANNOUNCER

Canada
4110 - 79th Street N.W.
Calgary, Alberta
Canada T3B 5C2
Tel: 403 288 2706
Toll Free 800 661 9406
Fax: 403 288 5935
info@interalia.com

United States
10340 Viking Drive,
Suite 135
Eden Prairie, Minnesota
U.S.A. 55344
Tel: 952 942 6088
Toll Free 800 531 0115
Fax: 952 942 6172
info@interalia.com

United Kingdom
Bridge End Road
Grantham, Lincolnshire
England NG31 7TS
Tel: +44 (0) 1476 594207
Fax: +44 (0) 1476 594208
info@interalia.com

Recording Time Available:

- 1 minute of recording time

Number of Lines:

- 1 line

Number of Messages:

- 1 and/or 2 announcement messages
- Both messages are user selectable
- Messages can be linked

Telephone Line Interface:

- Connector: RJ11C modular jack connector
- Line Activation:
 - Loop
 - Ground
 - Battery
 - E&M
 - Continuous play
- Off hook impedance: 600 ohm nominal
- Output level: High -10 dBm, Low -16 dBm

Audio Storage:

- Voice encoding/decoding: pulse code modulation (PCM)
- Storage medium: FLASH
- Sampling rate: 8 kHz, 8 bits/sample
- Frequency response: 300 Hz to 3.4 kHz (+/- 3 dB)

Audio Inputs:

- Handset: 90 mV to 600 mV @ 220 ohm impedance
- Tape: 150 mV to 1000 mV @10K ohm impedance

Power Supply:

- Input: 110/120 VAC or 220/240 VAC, 50/60 Hz, 20 W
- Output: 9 VDC @ 1 Amp

Dimensions:

- 1.75 in. (4.5 cm) H x 8 in. (20.3 cm) W x 8 in. (20.3 cm) D

Weight:

- 3.3 lbs (1.5 kg)

Approvals:

- FCC, CS-03, NRTL/C, BABT, CE

For more information visit: www.interalia.com

Interalia Delivering Messages: Simply, Clearly, Reliably

