

# iProMOH-One TECHNICAL SPECIFICATION

## Specifications

<b>Channels</b>	1
<b>Storage Capacity</b>	12 minutes, preloaded with 4 minutes royalty free music
<b>Play Options</b>	Music only, messages only, mixed music and messages.
<b>Media Update</b>	Via USB flash drive
<b>Firmware Update</b>	Via USB flash drive
<b>Volume Control</b>	Push button
<b>Trigger Input</b>	One 3.5mm female jack
<b>Audio Output</b>	One 3.5mm female jack
<b>Output Impedance (8 <math>\Omega</math> Load)</b>	Z=42 $\Omega$ with 1kHz test tone
<b>Output Impedance (600 <math>\Omega</math> Load)</b>	Z=75 $\Omega$ with 1kHz test tone
<b>Output Impedance (10 k<math>\Omega</math> Load)</b>	Z=125 $\Omega$ with 1kHz test tone
<b>Power Supply</b>	AC to USB adaptor with multi-region connectivity Input: 100-240 VAC, 50-60Hz, 0.2A Output: 5 VDC @ 1A

## Output Impedance

The output impedance of the iProMOH-One was optimized for older PBX systems. The impedances listed above are the active impedance values based on the specified test tone. Modern electronics utilize resistive amplification circuits, versus the reactive ones from older electronics, which eliminates the need for the input and output to be impedance matched.

**Questions? Visit [www.interalia.com](http://www.interalia.com) or contact us at:**

### Canada

6815 - 8<sup>th</sup> Street NE  
Calgary, AB T2E 7H7  
Phone: (403) 288-2706  
Toll Free: (800) 661-9406  
Fax: (403) 288-5935  
Email: [info@interalia.com](mailto:info@interalia.com)

### United States

701 - 24<sup>th</sup> Ave SE  
Minneapolis, MN 55414  
Phone: (403) 288-2706  
Toll Free: (800) 661-9406  
Fax: (403) 288-5935  
Email: [info@interalia.com](mailto:info@interalia.com)

### United Kingdom

58 Herschel Street  
Slough SL1 1HD  
United Kingdom  
Phone: +44 203 6082606  
Fax: (403) 288-5935  
Email: [info@interalia.com](mailto:info@interalia.com)



Delivering Messages: Simply. Clearly. Reliably.